

TX station: 6+6AkI5
Gain solid integration : enabled

Site Name: Labelitaly

General data of Antenna System

TX station	6+6AkI5
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	98.000
Antenna system central frequency (MHz)	98.000
Antenna base diagrams type 1	LABEL ITALY-AKL_5 LOG 5 ELEM. FM WB
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	AKL_5 LOG 5 ELEM.
Band start(MHz)	88
Band stop(MHz)	108
diagrams Frequency(MHz)	98
Polariz (H,V,C,X)	V
Vertical dist (cm)	260
Height (cm)	173
Width (cm)	6
Thickness (cm)	143
Weight (Kg)	4.5
Maximum power (KW)	2
Gain (dBd)	6.2
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	20
R.C.Phase (°)	0

TX station: 6+6AkI5
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)	<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	8.333	0	0	0 +0.0	6.50	80.0	270.0	1	1	0.0	0.0
2	8.333	0	0	0 +0.0	3.90	80.0	270.0	1	1	0.0	0.0
3	8.333	0	0	0 +0.0	1.30	80.0	270.0	1	1	0.0	0.0
4	8.333	0	0	0 +0.0	-1.30	80.0	270.0	1	1	0.0	0.0
5	8.333	0	0	0 +0.0	-3.90	80.0	270.0	1	1	0.0	0.0
6	8.333	0	0	0 +0.0	-6.50	80.0	270.0	1	1	0.0	0.0
7	8.333	0	0	0 +0.0	6.50	80.0	90.0	1	1	0.0	0.0
8	8.333	0	0	0 +0.0	3.90	80.0	90.0	1	1	0.0	0.0
9	8.333	0	0	0 +0.0	1.30	80.0	90.0	1	1	0.0	0.0
10	8.333	0	0	0 +0.0	-1.30	80.0	90.0	1	1	0.0	0.0
11	8.333	0	0	0 +0.0	-3.90	80.0	90.0	1	1	0.0	0.0
12	8.333	0	0	0 +0.0	-6.50	80.0	90.0	1	1	0.0	0.0

TX station: 6+6AkI5
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly

Plan of antenna system



Side of antenna system



TX station: 6+6AkI5
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly

Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	12
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	16.21
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	16.21
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	16.21
K. Effec. max gain (times)	41.83
L. Effec. max power [E * K] (KW)	41.8280
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	0

Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	16.2	90	-3.8	180	-3.8	270	-3.8
10	15.7	100	-3.8	190	-3.8	280	-3.8
20	14.4	110	-3.8	200	-3.8	290	-3.8
30	12.1	120	-3.8	210	-3.8	300	-3.8
40	8.6	130	-3.8	220	-3.8	310	3.5
50	3.5	140	-3.8	230	-3.8	320	8.6
60	-3.8	150	-3.8	240	-3.8	330	12.1
70	-3.8	160	-3.8	250	-3.8	340	14.4
80	-3.8	170	-3.8	260	-3.8	350	15.7


TX station: 6+6AkI5

Frequency: 98.00 MHz

Gain solid integration : enabled

Site Name: Labelitaly

Horizontal diagram at 0.0° depres. (Total Antenna)



0.0° depres. (Total Antenna), Gain (dBd): 16.21

ERP T.Max(KW): 41.828 ERP E.Max(KW): 41.828


TX station: 6+6AkI5

Frequency: 98.00 MHz

Gain solid integration : enabled

Site Name: Labelitaly

Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 16.21

ERP T.Max(KW): 41.828 ERP E.Max(KW): 41.828