

TX station: 2xBkr3

Gain solid integration : disabled

Site Name: Labelitaly

General data of Antenna System

TX station	2xBkr3
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	155.000
Antenna system central frequency (MHz)	155.000
Antenna base diagrams type 1	LABEL ITALY-BKR_3 YAGI 3 ELEM. VHF WB
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	BKR_3 YAGI 3 ELEM.
Band start(MHz)	140
Band stop(MHz)	174
diagrams Frequency(MHz)	155
Polariz (H,V,C,X)	V
Vertical dist (cm)	155
Height (cm)	109
Width (cm)	6
Thickness (cm)	88
Weight (Kg)	6
Maximum power (KW)	2
Gain (dBd)	5
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	20
R.C.Phase (°)	0

TX station: 2xBkr3
Frequency: 155.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)		<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	50.000	0	0	0	+0.0	0.90	0.0	0.0	1	1	0.0	0.0
2	50.000	0	0	0	+0.0	-0.90	0.0	0.0	1	1	0.0	0.0

TX station: 2xBkr3
Frequency: 155.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Plan of antenna system



Side of antenna system



TX station: 2xBkr3
Frequency: 155.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	2
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	8.01
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	8.01
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	8.01
K. Effec. max gain (times)	6.32
L. Effec. max power [E * K] (KW)	6.3246
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	0


Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	8.0	90	2.0	180	-5.4	270	2.0
10	8.0	100	0.3	190	-5.4	280	3.4
20	7.8	110	-1.3	200	-5.3	290	4.7
30	7.5	120	-2.8	210	-5.1	300	5.8
40	7.2	130	-3.8	220	-4.6	310	6.6
50	6.6	140	-4.6	230	-3.8	320	7.2
60	5.8	150	-5.1	240	-2.8	330	7.5
70	4.7	160	-5.3	250	-1.3	340	7.8
80	3.4	170	-5.4	260	0.3	350	8.0

TX station: 2xBkr3
Frequency: 155.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Horizontal diagram at 0.0° depres. (Total Antenna)




0.0° depres. (Total Antenna), Gain (dBd): 8.01

ERP T.Max(KW): 6.3246 ERP E.Max(KW): 6.3246

TX station: 2xBkr3
Frequency: 155.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 8.01

ERP T.Max(KW): 6.3246 ERP E.Max(KW): 6.3246