

TX station: 2xAkh1

Gain solid integration : disabled

Site Name: Labelitaly

General data of Antenna System

TX station	2xAkh1
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	98.000
Antenna system central frequency (MHz)	98.000
Antenna base diagrams type 1	LABEL ITALY-AKH_1 DIPOLE FM WB
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	AKH_1 DIPOLE FM WB
Band start(MHz)	88
Band stop(MHz)	108
diagrams Frequency(MHz)	98
Polariz (H,V,C,X)	V
Vertical dist (cm)	260
Height (cm)	140
Width (cm)	6
Thickness (cm)	90
Weight (Kg)	4.5
Maximum power (KW)	2
Gain (dBd)	2.16
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	20
R.C.Phase (°)	0

TX station: 2xAkh1
Frequency: 98.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)		<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	50.000	0	0	0	+0.0	1.30	0.0	0.0	1	1	0.0	0.0
2	50.000	0	0	0	+0.0	-1.30	0.0	0.0	1	1	0.0	0.0

TX station: 2xAkh1
Frequency: 98.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Plan of antenna system



Side of antenna system



TX station: 2xAkh1
Frequency: 98.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	2
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	5.17
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	5.17
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	5.17
K. Effec. max gain (times)	3.29
L. Effec. max power [E * K] (KW)	3.2887
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	340


Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	5.2	90	2.3	180	-1.0	270	2.3
10	5.2	100	1.4	190	-1.0	280	3.1
20	5.2	110	0.5	200	-0.9	290	3.9
30	5.1	120	-0.1	210	-0.9	300	4.4
40	5.0	130	-0.5	220	-0.7	310	4.8
50	4.8	140	-0.7	230	-0.5	320	5.0
60	4.4	150	-0.9	240	-0.1	330	5.1
70	3.9	160	-0.9	250	0.5	340	5.2
80	3.1	170	-1.0	260	1.4	350	5.2

TX station: 2xAkh1
Frequency: 98.00 MHz
Gain solid integration : disabled

Site Name: Labelitaly

Horizontal diagram at 0.0° depres. (Total Antenna)



0.0° depres. (Total Antenna), Gain (dBd): 5.17 ERP T.Max(KW): 3.2887 ERP E.Max(KW): 3.2887


TX station: 2xAkh1

Frequency: 98.00 MHz

Gain solid integration : disabled

Site Name: Labelitaly

Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 5.17

ERP T.Max(KW): 3.2887 ERP E.Max(KW): 3.2887