

TX station: 6xAkk2

Gain solid integration : enabled

Site Name: Labelitaly

General data of Antenna System

TX station	6xAkk2
Site Name	Labelitaly
System of coordinates	Geographic
Longitude	00°00'00.000"
Latitude	00°00'00.000"
Ground level a.s.l. (m)	100.0
Antenna system height (m)	50.0
Transmitter power(Watt)	1000.000
Carrier wave frequency (MHz)	98.000
Antenna system central frequency (MHz)	98.000
Antenna base diagrams type 1	LABEL ITALY-AKK_2V PANEL W.B. FM vertical pol.
Antenna base diagrams type 2	-
Polarization (H/V/C/X)	V
Transmitting cable attenuation (dB)	0.0
Additional attenuations(dB)	0.0
Base diagrams sectors (T = All, F = Front)	T
Velocity factor of cables to Antennas (0÷1)	0.88
Coordinate System(C = cartesian, P = polar)	P
Mast side / diameter(cm):	10.0
Mast cross section (T/Q/C)	C
Structure rotation w.r.t. North (°)	0.0
Mast rotation w.r.t. North (°)	0.0

Information about antennas used in the System

	<i>Antenna type 1</i>
Manufacturer	LABEL ITALY
Antenna model	AKK_2V PANEL W.B. F
Band start(MHz)	88
Band stop(MHz)	105
diagrams Frequency(MHz)	98
Polariz (H,V,C,X)	V
Vertical dist (cm)	310
Height (cm)	174
Width (cm)	248
Thickness (cm)	80
Weight (Kg)	45
Maximum power (KW)	5
Gain (dBd)	8.1
North E.C. (cm)	0
East E.C. (cm)	0
Return loss (dB)	0
R.C.Phase (°)	0

TX station: 6xAkk2
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly


Geometr. and electrical data of Antenna System

	<i>Power</i> (%)	<i>Tilt</i> (°)	<i>Az.</i> (°/N)	<i>Phase</i> (°)	<i>V dist.</i> (m)	<i>Scr-d</i> (cm)	<i>Scr-Az</i> (°/N)	<i>Rot.</i> (1÷4)	<i>Type</i> (1÷2)	<i>L cables</i> (cm)	<i>Car. phase</i> (°)
1	16.667	0	0	0 +0.0	7.00	0.0	0.0	1	1	0.0	0.0
2	16.667	0	0	0 +0.0	4.20	0.0	0.0	1	1	0.0	0.0
3	16.667	0	0	0 +0.0	1.40	0.0	0.0	1	1	0.0	0.0
4	16.667	0	0	0 +0.0	-1.40	0.0	0.0	1	1	0.0	0.0
5	16.667	0	0	0 +0.0	-4.20	0.0	0.0	1	1	0.0	0.0
6	16.667	0	0	0 +0.0	-7.00	0.0	0.0	1	1	0.0	0.0

TX station: 6xAkk2
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly

Plan of antenna system



Side of antenna system



TX station: 6xAkk2
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly

Antennas arrays data

A. Antennas array azimuth (°/N)	0
B. Number of antennas	6
C. Nominal power supply (W)	1000.00
D. Losses (addit. + cables) (dB)	0.0
E. Effective power supply (W)	1000.00
F. Theor. maximum gain (dBd)	15.79
G. Distribution losses (dB)	0.00
H. Nominal max gain [F - G] (dBd)	15.79
I. Compensation losses (dB)	0.00
J. Effec. max gain [H - I] (dBd)	15.79
K. Effec. max gain (times)	37.96
L. Effec. max power [E * K] (KW)	37.9627
M. Max power depr. angle (°)	0.0
N. Max power az. angle (°)	358


Diagram in dBK calculated at horizon

Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK	Az. (°/N)	dBK
0	15.8	90	-4.2	180	-4.2	270	-4.2
10	15.4	100	-4.2	190	-4.2	280	-4.2
20	14.5	110	-4.2	200	-4.2	290	-1.3
30	12.8	120	-4.2	210	-4.2	300	2.6
40	9.6	130	-4.2	220	-4.2	310	6.4
50	6.4	140	-4.2	230	-4.2	320	9.6
60	2.6	150	-4.2	240	-4.2	330	12.8
70	-1.3	160	-4.2	250	-4.2	340	14.5
80	-4.2	170	-4.2	260	-4.2	350	15.4

TX station: 6xAkk2
Frequency: 98.00 MHz
Gain solid integration : enabled

Site Name: Labelitaly

Horizontal diagram at 0.0° depres. (Total Antenna)



0.0° depres. (Total Antenna), Gain (dBd): 15.79 ERP T.Max(KW): 37.9627 ERP E.Max(KW): 37.9627


TX station: 6xAkk2

Frequency: 98.00 MHz

Gain solid integration : enabled

Site Name: Labelitaly

Vertical diagram at an azimuth of 0.0° degrees



0.0° Az. (Total Antenna), Gain (dBd): 15.79

ERP T.Max(KW): 37.9627 ERP E.Max(KW): 37.9627